

Transmission of Slow Light through Photonic Crystal Waveguide Bends

Solomon Assefa, Sharee J. McNab, and Yurii A. Vlasov¹

¹*IBM T. J. Watson Research Center, Yorktown Heights, NY 10598, USA*

(Dated: February 2, 2008)

The spectral dependence of a bending loss of cascaded 60-degree bends in photonic crystal (PhC) waveguides is explored in a slab-type silicon-on-insulator system. Ultra-low bending loss of (0.05 ± 0.03) dB/bend is measured at wavelengths corresponding to the nearly dispersionless transmission regime. In contrast, the PhC bend is found to become completely opaque for wavelengths range corresponding to the slow light regime. A general strategy is presented and experimentally verified to optimize the bend design for improved slow light transmission.

Planar two-dimensional photonic crystal (PhC) waveguides have a strong potential to realize ultra-dense photonic integrated-circuits. An important component of a compact photonic circuit is a small-radius low-loss waveguide bend that efficiently maneuvers light around sharp corners¹. Many papers have investigated PhC bends focusing mainly on the optimization of the amplitude transmission². Largely ignored, however, is the spectral dependence of the bend loss. It is known that PhC waveguides are characterized by very large group velocity dispersion especially at wavelengths close to the onset of the waveguiding mode^{10,11}. The strong distributed feedback at these wavelengths results in significantly reduced group velocity. The possibility to slow down the propagation of light is envisioned to have a broad range of applications from all-optical data storage to quantum computing¹². Therefore transmission in this "slow light" regime needs to be carefully studied for various optical components, if the "slow light"-based circuits are to be built. This paper focuses on the spectral dependence of losses of PhC bends with a special emphasis on the "slow light" regime.

The PhC waveguides were fabricated on 200mm silicon-on-insulator (SOI) wafers with $2\mu\text{m}$ thick buried oxide (BOX) and 220nm thick silicon layer. The periodic array of holes with a triangular lattice (lattice constant $a=437\text{nm}$) was first written in the resist layer with electron beam lithography. The PhC waveguides were formed by removing a row of holes in the Γ -K direction of the lattice. The pattern was then transferred to an oxide hard mask using $\text{CF}_4/\text{CHF}_3/\text{Ar}$ chemistry and the Si layer was etched next with an HBr-based chemistry. The underlying BOX was wet etched in the PhC section to create a suspended Si membrane. An additional lithography step defined the polymer cladding of the inverted taper spot-size converter for efficient fiber coupling^{13,14}.

In order to improve the experimental accuracy of loss measurements, devices with a number of bends cascaded in series were fabricated as shown in Fig.1a. The bends were separated from each other by straight waveguide sections 20 lattice constants long. To optically characterize the devices, light from a broadband LED source (1200 to 1700nm) is coupled to the PM fiber, transferred




FIG. 1: Scanning electron micrographs of a PhC waveguide structures. A) 10 cascaded 60-degree bends, B) Magnified view of a simple 60-degree bend, C) Magnified view of a modified 60-degree bend with four holes adjacent to the bend corner having smaller radii.

through the polarization controller and finally launched into the device with a microlensed PM fiber tip. Transmission spectra were measured for the TE polarization (E-field parallel to the slab plane) with a resolution of 5nm. The measured transmission spectra through straight and bent PhC waveguides were normalized on transmission through a reference straight strip waveguide following the method of Ref.¹³.

The design of the PhC bend similar to the one shown in Fig.1b was characterized first. This simple bend is formed by connecting two W1 waveguides rotated by 60 degrees with respect to each other. Figure 2 represents




FIG. 2: Transmission spectra for PhC structures with hole radius of 100nm (0.23a). A) Spectrum (black curve) of a straight PhC waveguide with a length of 181 μ m and spectra of structures with 10 (blue curve) and 20 (red curve) cascaded simple bends. Inset: Set of spectra measured on ten different devices with 10 (red curves) and 20 (blue curves) cascaded simple bends. B) Photonic band diagram for a PhC waveguide with a radius of holes 0.23a and a slab thickness of 0.52a.

experimental transmission spectra of 10 and 20 of such cascaded simple bends formed in a PhC lattice with a hole radius of 100nm (0.23a). The spectra show a transmission band with 50nm bandwidth defined by two sharp cut-offs around 1605 and 1655nm. Spectra measured for 10 and 20 cascaded bends are almost identical, especially for 1627-1635nm spectral region shown in the inset in magnified view, indicating low bending loss. Statistical analysis of measurements performed on a number of identical devices gives a cumulative loss of 0.55dB per 10 bends that includes a small loss component of 0.07dB which is the expected loss of a straight PhC waveguide sections of equivalent length (90 μ m)¹⁴. The standard deviation is estimated for these measurements as 0.33dB, owing mainly to the small deviation in the coupling efficiency from one device to another. This gives the bending loss per single bend of (0.05 $\pm$ 0.03)dB/bend. To our knowledge this is the lowest bending loss that has yet been reported for PhC bends.

If bends are to be used to construct complex PhC-based circuits such as a Mach-Zehnder interferometer employing straight PhC waveguides and multiple bends, transmission characteristics of the bend need to be analyzed with respect to different transmission regimes of a straight PhC waveguide. The black curve in Fig.2a represents the transmission spectrum of a 181 μ m long

straight PhC waveguide which corresponds to the same length as the devices with 20 cascaded bends. Comparison of the experimental spectrum with the photonic band structure calculated with the 3D plane-wave method¹⁵ shown in Fig.2b allows identification of the sharp cut-off at 1687nm as the onset of the waveguiding mode. The waveguide is characterized by very strong group velocity dispersion with a group index becoming increasingly large in the region 1660nm-1687nm. This region can be defined as the "slow light" regime (region I in Fig.2b). The dispersion is almost linear, corresponding to nearly constant group index, in the wavelength region between 1660nm and 1560nm, which can be defined as the "linear" regime (region II). At wavelengths above 1560nm (region III), where the mode is crossing the light-line, the losses are increasing progressively due to out-of-plane leakage.

The transmission spectra of the bend exhibit drastically different behavior for wavelengths corresponding to the three regimes. At wavelengths corresponding to region III, where the mode is becoming leaky for the straight PhC waveguide, the bend does not transmit any light as shown in Fig.2a presumably due to significant increase in out-of-plane losses at the bend. However, since the loss for a straight PhC waveguide is already very large here, approaching 1500dB/cm^{13,14}, region III is not very useful for integrated photonics.

In contrast, bending loss in the "linear" regime (region II) is extremely small not exceeding 0.05dB/bend as demonstrated above. This low bending loss is comparable to bending losses measured in tightly curved bends in single-mode strip waveguides¹⁶. However, as opposed to strip waveguide bends operating over broadband wavelengths, the PhC bend does not have a continuous transmission band. In Fig.2a at wavelengths corresponding to region II a series of sharp dips are seen with attenuation significantly increasing as the number of cascaded bends increases, indicating much higher bending loss of the order of 1dB/bend. These dips result from small stopbands formed in the experimental optical circuit in which straight and bend sections are repeated periodically.

Attaining low bending loss in the region I is crucial for constructing optical circuits utilizing slow group velocity. Surprisingly, comparison of transmission spectra (Fig.2a) of a straight PhC waveguide and PhC bends reveals that bends are completely opaque in this region. The long-wavelength cutoff of the bend around 1655nm appears to be blue shifted by 30nm (blue arrow) with respect to the 1687nm cutoff characteristic of the straight PhC waveguide. This blueshift is too large to be explained by small variation of the lattice parameters between reference PhC straight waveguide and the bend structure. Moreover, detailed inspection of a number of SEM images as in Fig.1 reveals that the hole radii and the lattice constant in both structures are identical within 1nm.

This spectral blueshift can be explained by making analogy to conventional strip and rib waveguide bends¹⁷. It is known that the mode in curved waveguides is pulled




FIG. 3: Transmission spectra for PhC structures with a hole radius of 144nm (0.33a). A) Spectrum (black curve) of a straight PhC waveguide with a length of 181 μ m and spectra of structures with 10 (blue curve) and 20 (red curve) cascaded simple bends. B) Spectra of structures with 10 (blue curve) and 20 (red curve) cascaded modified bends. Arrows indicate a blueshift of the cutoff.

away from the center of curvature toward the outer edge of the bend, thus seeing a lower average refractive index with respect to the mode in the straight waveguide¹⁷. If this mechanism can be extended to describe mode behavior in PhC waveguide bends, the PhC Bloch mode is pulled toward its outer corner where it samples more holes. Hence, the average refractive index that the mode encounter at the bend is smaller, which explains the experimentally observed blueshift of the cutoff. In integrated optics, the usual way to compensate the distortion of the mode profile at the bend is to offset the bend section with respect to the straight section or to increase the refractive index at the bend by increasing its width¹⁷. Recent theoretical calculations have confirmed that a similar hypothesis is applicable to PhC waveguide bends¹⁸. A modified design is proposed where the average refractive index at the bend is effectively increased by decreasing the radius of holes in the bend vicinity¹⁸.

To experimentally verify this strategy, an additional set of devices was investigated, fabricated on the same wafer as the previous devices. The hole radii of the PhC lattice for this set was chosen to be 144nm (0.33a) in order to compare the experimental results directly to the theoretical calculations of Ref.¹⁸. This device set consisted of cascaded simple bends analogous to that studied earlier (see Fig.1b), and the cascaded modified bends

(Fig.1c) designed for better transmission in the slow light regime¹⁸.

Figure 3a shows transmission spectra of a straight PhC waveguide and a simple cascaded PhC bends. The low-loss transmission window for a straight PhC waveguide is defined by a long-wavelength cutoff at 1493nm and a light-line at 1466nm. Band structure calculations similar to Fig.2b showed that the "slow light" regime I in this case corresponds to wavelengths range of 1478nm-1493nm. Similar to the results obtained in Fig.2a, the spectrum of the simple bend is characterized by a relatively low-loss transmission band extending over the "linear" regime and interrupted by sharp dips. The long-wavelength cutoff of a bend spectrum at 1478nm is blue shifted by almost 15nm with respect to the cutoff position in a straight PhC waveguide. Thus, the simple bend in this structure appears to be completely opaque in the "slow light" regime as previously observed in the results of Fig.2.

Figure 3b represents spectra of 10 and 20 cascaded bends, which are modified by reducing the radius of four holes adjacent to the bend section to 105nm (0.24a) as shown in Fig.1c. Transmission spectra of 10 and 20 cascaded modified bends have similar spectral features as seen in the spectrum of a simple bend. The "linear" regime of a modified bend is characterized by a relatively low loss 0.1dB/bend comparable to the results of Fig.2a. As expected, the long-wavelength cutoff of the modified bend occurs at wavelengths longer than for a simple bend. Hence, by increasing the average refractive index at the bend the initial 15nm blueshift of the cutoff is significantly reduced to only 6nm rendering a large portion of the "slow light" regime transparent.

The modified bends with 4 small holes clearly do not fully compensate the initial blueshift. The experiments described above can be viewed as a proof-of-principle demonstration of a general strategy, rather than a final solution. Following the analogy with the bends in conventional waveguides, the transmission in the "slow light" regime might be improved not only by the increase of the refractive index at the bend as shown here, but also by creating an offset of the bend section with respect to the straight PhC waveguide.

In conclusion, ultra-low bending loss of only (0.05 ± 0.03) dB/turn is measured in a simple 60-degree PhC bend. It is found that simple PhC bends are completely opaque for the wavelength region corresponding to small group velocity regime of a straight PhC waveguide. Increasing the average refractive index at the bend by decreasing the radius of 4 holes adjacent to the bend section allows to almost compensate the blueshift of the transmission cutoff and to restore transparency for slow light.

Discussions with Drs. N. Moll and G.-L. Bona are gratefully acknowledged. This work was partially supported by DARPA/ONR (DSO, J. Lowell) through grant No.00014-04-C-0455.

-
- ¹ A. Mekis, J.C. Chen, I. Kurkland, S. Fan, P. R. Villeneuve, and J. D. Joannopoulos, "High Transmission through Sharp Bends in Photonic Crystal Waveguides", *Phys. Rev. Lett.* 77, 3787 (1996).
 - ² T. Baba, N. Fukaya and J. Yonekura "Observation of light propagation in photonic crystal optical waveguides with bends", *Electron. Lett.* 35, 654 (1999)
 - ³ M. Loncar, D. Nedeljkovic, T. Doll, J. Vuckovic, A. Scherer, T.P. Pearsall, "Waveguiding in planar photonic crystal", *Appl. Phys. Lett.* 77 1937 (2000)
 - ⁴ E. Chow, S. Y. Lin, J. R. Wendt, S. G. Johnson, J. D. Joannopoulos, "Quantitative analysis of bending efficiency in photonic-crystal waveguide bends at $\lambda = 1.55\mu\text{m}$ wavelengths," *Opt. Lett.* 26, 286-288 (2001).
 - ⁵ Chutinan, M. Okano, S. Noda, "Wider bandwidth with high transmission through waveguide bends in two-dimensional photonic crystal slabs," *Appl. Phys.Lett.* 80, 1698 (2002)
 - ⁶ L.H. Frandsen, A. Harph, P.I. Borel, M. Kristensen, J.S. Jensen and O. Sigmund, "Broadband photonic crystal waveguide 60 bend obtained utilizing topology optimization", *Opt. Express* 12, 5916 (2004).
 - ⁷ I. Ntakis, P. Pottier, and R. M. De La Rue, "Optimization of transmission properties of two-dimensional photonic crystal channel waveguide bends through local lattice deformation", *J. Appl. Phys.* 96, 12 (2004)
 - ⁸ B. Miao, C. Chen, S. Shi, J. Murakowski, and D. W. Prather, "High-Efficiency Broad-Band Transmission Through a Double-60 Bend in a Planar Photonic Crystal Single-Line Defect Waveguide", *IEEE Photon. Techn. Lett.* 16 2469 (2004)
 - ⁹ N. Ikeda, Y. Sugimoto, Y. Tanaka, K. Inoue, and K. Asakawa, "Low Propagation Losses in Single-Line-Defect Photonic Crystal Waveguides on GaAs Membrane" *IEEE J. Sel. Areas Comm.* 23, 1315 (2005).
 - ¹⁰ M. Notomi, K. Yamada, A. Shinya, J. Takahashi, C. Takahashi, and I. Yokohama "Extremely Large Group-Velocity Dispersion of Line-Defect Waveguides in Photonic Crystal Slabs" *Phys. Rev. Lett.* 87, 253902 (2001)
 - ¹¹ Yu. A. Vlasov, M. O'Boyle, H. F. Hamann, S. J. McNab, "Taming slowlight in photonic crystal waveguides" accepted for publication (2005)
 - ¹² M. Yanik, W. Suh, Z. Wang, and S. Fan, "Stopping Light in a Waveguide with an All-Optical Analog of Electromagnetically Induced Transparency", *Phys. Rev. Lett.* 93, 233903 (2004)
 - ¹³ S. J. McNab, N. Moll and Yu. A. Vlasov, "Ultra-low loss photonic integrated circuit with membrane-type photonic crystal waveguides", *Opt. Express*, 11, 2927 (2003)
 - ¹⁴ E. Dulkeith, S.J. McNab and Yu.A. Vlasov "Mapping the optical properties of slab-type two-dimensional photonic crystal waveguides", *Phys. Rev. B* 72, 15 Sep (2005).
 - ¹⁵ S. G. Johnson and J. D. Joannopoulos, "Block-iterative frequency-domain methods for Maxwell's equations in a planewave basis," *Opt. Express* 8, 173 (2001).
 - ¹⁶ Y. A. Vlasov and S. J. McNab, "Losses in single-mode silicon-on-insulator strip waveguides and bends," *Opt. Express* 12, 1622 (2004).
 - ¹⁷ M. K. Smit, E. C. M. Pennings, H. Blok "A Normalized Approach to the Design of Low-Loss Optical Waveguide Bends", *Journ. Lightwave Techn.* 11, 1737 (1993)
 - ¹⁸ N. Moll, G.-L. Bona, "Bend design for the low-group-velocity mode in photonic crystal-slab waveguides", *Appl. Phys. Lett.* 85, 4322 (2004)